

QUICKTRONIC MULTIWATT

ECE para CFL



Áreas de aplicación

- Edificios públicos
- Pabellones deportivos y fábricas
- Apto para luminarias con clase de protección I

Beneficios del producto

- Larga vida útil
- Sin efectos adversos por conexiones y desconexiones frecuentes
- Reencendido automático tras el reemplazo de lámpara
- Perfecto arranque de las lámparas para aplicaciones con sensores de movimiento
- Instalaciones por separado, gracias a la clema para cables para las carcasas K2 y K3
- Sistema certificado VDE/VDE CEM

Características del producto

- Tensión de suministro: 220...240 V
- Tensión de línea: 198...264 V
- Frecuencia de línea: 0 Hz | 50 Hz | 60 Hz
- Arranque de las lámparas con óptimo precalentamiento de filamento
- Índice de eficiencia energética EEI: A2
- Desconexión automática de lámparas defectuosas y al final de su vida útil (EoL T.2)
- Funcionamiento de la lámpara: según EN 60929
- Seguridad: según EN 61347-2-3

Hoja de datos gama de productos

Consejos de aplicación

Para más información detallada sobre la aplicación y gráficos vea la hoja de datos del producto.

Texto de la hoja técnica

- In order to achieve good radio interference suppression:1. Keep the cable between ECG and lamp as short as possible.2. The single lamp wires must be routed as close as possible to each other, whereas the lines of the different lamp ends must be routed separately.

Soporte ventas y técnico

Soporte ventas y técnico www.osram.es

Ecodesign regulation information:

Separate control gear and light sources must be disposed of at certified disposal companies in accordance with Directive 2012/19/EU (WEEE) in the EU and with Waste Electrical and Electronic Equipment (WEEE) Regulations 2013 in the UK. For this purpose, collection points for recycling centres and take-back systems (CRSO) are available from retailers or private disposal companies, which accept separate control gear and light sources free of charge. In this way, raw materials are conserved and materials are recycled.

Aviso

Sujeto a cambios sin aviso. Excepto errores y omisiones. Asegúrese de utilizar la emisión más reciente.