

D4i, DEXAL, AstroDIM, StepDIM - constant current LED drivers



- Rango de salida de corriente: 70...1.050 mA
- Consumo eléctrico en stand-by: < 0,5 W

- For Zhaga Book18 Luminaires and D4i certified incl. Parts 25x + AUX
- Baja tolerancia de eficacia luminosa a través de la baja salida de tolerancia de corriente de $\pm 3 \%$

- Iluminación de calles y urbana
- Industria
- Apto para aplicaciones en exteriores en luminarias con IP > 54
- Apto para el uso en luminarias en exteriores con clase de protección I y II

Consejos de aplicación

Para más información detallada sobre la aplicación y gráficos vea la hoja de datos del producto.

Texto de la hoja técnica

- Shut down of output load happens if the input voltage of the load is below the allowed minimum output voltage of the driver. The driver automatically tries to switch on the load cyclically.
 - The driver automatically reduces the output current in case the maximum allowed output power is exceeded, as long as the input voltage of the load is within the declared output voltage range of the driver. In all other cases the driver may shut down the load.
 - The driver is protected against temporary overheating by automatic reduction of the output current.
 - Several external NTCs are supported for temperature protection of the LED module or luminaire. The type of NTC can be selected in the programming software in the temperature based mode. By default the resistor based mode is activated with following values: start derating: 6.3 kOhm, end derating 5.0 kOhm, shut off: 4.3 kOhm, derating level 50 %.
 - The constant lumen feature is disabled by default.
 - If any output level is below the physical min level, the physical min level will be used.
 - not relevant
 - The DEXAL interface is polarity sensitive, even if the DEXAL bus power supply in the driver is turned off. Therefore the polarity of all connected drivers should not be mixed.
 - For efficiency and standby power measurement, the D4i bus power supply shall be switched off by using Tuner4TRONIC. Refer to www.tuner4tronic.com.
-

Soporte ventas y técnico

Soporte ventas y técnico www.osram.es

Ecodesign regulation information:

Intended for use with LED modules.

The forward voltage of the LED light source shall be within the defined operating window of the control gear in all operating conditions including dimming if applicable.

Separate control gear and light sources must be disposed of at certified disposal companies in accordance with Directive 2012/19/EU (WEEE) in the EU and with Waste Electrical and Electronic Equipment (WEEE) Regulations 2013 in the UK. For this purpose, collection points for recycling centres and take-back systems (CRSO) are available from retailers or private disposal companies, which accept separate control gear and light sources free of charge. In this way, raw materials are conserved and materials are recycled.

Aviso

Sujeto a cambios sin aviso. Excepto errores y omisiones. Asegúrese de utilizar la emisión más reciente.
